

2301-SERIES KEY SERVICE UNITS IDENTIFICATION AND CONNECTIONS

1.00 GENERAL

1.01 This section covers identification and connections of 2301-series key service units.

1.02 The 2301-series key service units are Distributing House converted cable-tail-equipped 200F-type key telephone units. Converted units closely approximate in appearance and performance the comparable 301-series key service units.

1.03 Conversion consists essentially of replacing the 173B backboard and external (64A1-50) cable terminal with a die-cast aluminum (177A) backboard equipped with two 66B1-25 connecting blocks. Two metal details are added for fastening and strengthening the hinge assembly of the 31A apparatus mounting to the new backboard. The cable tail is cut and reterminated on the 66B1-25 connecting blocks. Preprinted pressure-sensitive tapes (P-16C199 for block A and P-16C200 for block B) are applied to the fanning strips and show proper lead designations. These components (177A backboard, 66B1-25 connecting blocks, pressure-sensitive tapes, and two metal details) constitute and are obtainable as a D-179862 kit assembly.

1.04 The code numbering assignment for the 2301-series key service units correlates the original 200F-type key telephone unit to its nearest equivalent 301-series key service unit. For instance, the 200F4C key telephone unit after conversion would be coded a 2301A2 key service unit. Table A lists the converted codes.

1.05 By application of the ED-69462-01 cabinet assembly and/or A75A connector cable with 2301-series key service units, combinations other than those listed in Table A could be derived locally as necessary. Table A in section entitled Key Service Units, 300, 301, 302, 310, and 311 Types, Identification and Description offers a reference guide for applying appropriate 2301 and/or 2302-series key service units.

TABLE A

**200F-SERIES CODE SUPERSEDED BY
2301 SERIES**


Features	200F-Series Code	2301-Series Code
4 lines, man. intercom	200F4C	2301A2
4 lines, man. and dial intercom	200F4DC	2301A2D
5 lines, man. intercom	200F5C	2301A6
6 lines, man. intercom	200F6C	2301A10

2.00 CONNECTIONS

2.01 Connections for terminating running and/or key cables and external power wiring to the 66B1-25 connecting blocks are shown in Table B. Table B also shows interwiring of connections between the individual key telephone units and the connecting blocks.

2.02 For information on 66B1-25 connecting blocks see section entitled Connecting Blocks—66 Type.

2.03 For maintenance of converted key service units refer to Table B of this section and the appropriate figures in section entitled 200F-Type Key Telephone Units.



No new wiring changes are involved when converting 200F-type key telephone units to 2301-series key service units other than those concerned in the retermination of the original external cable tail on 66B1-25 connecting blocks inside the package.

TABLE B**2301-SERIES KEY SERVICE UNIT CONNECTIONS BETWEEN APPARATUS AND 66B1-25 CONNECTING BLOCKS**

Feature	Lead Desig	Block A 66B1-25 Connecting Block			Term. on 232A or B KTU*	Term. on KTU		Term. on 202C or D KTU	Term. on 207C KTU
		Term.	Clip	Cable Color Blue Binder		230A	230B†		
Line 1	T	1	6	W-BL		1A			
	R	2		BL-W		2A			
	A	3		W-O		3A			
	A1	4		O-W		4A			
	LG	5		W-G		6A			
	L	6		G-W		5A			
Line 2	T	7		W-BR		1B			
	R	8		BR-W		2B			
	A	9		W-S		3B			
	A1	10		S-W		4B			
	LG	11		R-BL		6B			
	L	12		BL-R		5B			
Line 3	T	13		R-O		1C			
	R	14		O-R		2C			
	A	15		R-G		3C			
	A1	16		G-R		4C			
	LG	17		R-BR		6C			
	L	18		BR-R		5C			
Line 4	T	19		R-S		1D			
	R	20		S-R		2D			
	A	21		BK-BL		3D			
	A1	22		BL-BK		4D			
	LG	23		BK-O		6D			
	L	24		O-BK		5D			

*232B KTU is arranged internally to disable time-out feature when BF relay is operated.

† 230B KTU is arranged for individual fusing of circuits 1-2 and 3-4 lamp input power.

TABLE B (Cont)


Feature	Lead Desig	Block A 66B1-25 Connecting Block			Term. on 232A or B KTU*	Term. on KTU		Term. on 202C or D KTU		Term. on 207C KTU
		Term.	Clip	Cable Color Blue Binder		230A	230B†			
Line 5	T	25	↑ 							

*232B KTU is arranged internally to disable time-out feature when BF relay is operated.

† 230B KTU is arranged for individual fusing of circuits 1-2 and 3-4 lamp input power.


‡ With 1 to 72 lamps, strap terminals 41, 42, and 44; with 73 to 144 lamps, strap terminals 42 and 44 and run separate power lead to 41.

TABLE B (Cont)

Feature		Lead Desig	Block B 66B1-25 Connecting Block			Term. on 232A or B KTU	Term. on KTU		Term. on 202C or D KTU		Term. on 207C KTU	
			Term.	Clip	Cable Color Orange Binder		230A	230B				
Manual Intercom Line		T	1		W-BL	30						
		R	2		BL-W	40						
		LG L			3	W-O	*					
					4	O-W	28					
Audible Signal	Line 1	B1 or BZ1	5		W-G		25A	30A				
		R1 or BZ	6		G-W		10A	10A				
	Line 2	B1 or BZ1	7		W-BR		25A					
		R1 or BZ	8		BR-W		10B					
	Line 3	B1 or BZ1	9		W-S		28A	30A				
		R1 or BZ	10		S-W		10C	10C				
	Line 4	B1 or BZ1	11		R-BL		28A	25A				
R1 or BZ		12	BL-R		10D		10D					
Line 5	B1 or BZ1	13	R-O					25	1st			
	R1 or BZ	14	O-R					10				
Line 6	B1 or BZ1	15	R-G					25	2nd			
	R1 or BZ	16	G-R					10				
Dial Selective Intercom Line		T	17		R-BR						1B 2B	
		R	18		BR-R							
		LG L			19	R-S						32B 3B
					20	S-R						
		B (2) R (2)			21	BK-BL						36B 12A
					22	BL-BK						
		B (3) R (3)			23	BK-O						36B 13A
					24	O-BK						
		B (4) R (4)			25	BK-G						37B 14A
					26	G-BK						
		B (5) R (5)			27	BK-BR						37B 15A
					28	BR-BK						
		B (6) R (6)			29	BK-S						38B 16A
					30	S-BK						
		B (7) R (7)			31	Y-BL						38B 17A
					32	BL-Y						

* Connect to convenient lamp ground.

TABLE B (Cont)

Feature		Lead Desig	Block B 66B1-25 Connecting Block			Term. on 232A or B KTU	Term. on KTU		Term. on 202C or D KTU		Term. on 207C KTU
			Term.	Clip	Cable Color Orange Binder		230A	230B			
Dial Selective Intercom Line		B (8)	33		Y-O						40B
		R (8)	34		O-Y						18A
		B (9)	35		Y-G						40B
		R (9)	36		G-Y						19A
		B (0)	37		Y-BR						31B
R (0)	38	BR-Y							20A		
CO or PBX	Line 1		39 40	Y-S S-Y		7A 8A					
	Line 2		41 42	V-BL BL-V		7B 8B					
	Line 3		43 44	V-O O-V		7C 8C					
	Line 4		45 46	V-G G-V		7D 8D					
	Line 5		47 48	V-BR BR-V			7 8	1st			
	Line 6		49 50	V-S S-V			7 8	2nd			